

Fusedrawer for Fuse Links 5x20 mm resp. 6.3x32 mm



Fuse drawer "Fingergrip" with voltage selector  
 (Fuse links not enclosed)

Fuse drawer "Extrasafe" without voltage selector  
 (Fuse links not enclosed)

See below:  
[Approvals and Compliances](#)

**Description**

- Component :  
 Snap-in , Rear Mounting
- 2 Functions :  
 Fuseholder for Fuse-links 5x20 mm or 6.3x32 mm , Voltage selector insert
- Approved together with power entry module

**Characteristics**

- Fuse drawer not enclosed, it must be ordered separately (see required accessories)
- Suitable for use in equipment according to IEC/UL 62368-1

**Other versions on request**

- Fuse drawer with other voltage values

**References**

Fits to type: [CD](#); [CD-Bowdencable](#); [KD](#); [KD-Bowdencable](#); [KEC](#); [KFC](#)

**Weblinks**

[pdf data sheet](#), [html datasheet](#), [General Product Information](#), [Approvals](#), [Distributor-Stock-Check](#), [Accessories](#), [Detailed request for product](#)

**Approvals and Compliances**

Detailed information on product approvals, code requirements, usage instructions and detailed test conditions can be looked up in [Details about Approvals](#)

SCHURTER products are designed for use in industrial environments. They have approvals from independent testing bodies according to national and international standards. Products with specific characteristics and requirements such as required in the automotive sector according to IATF 16949, medical technology according to ISO 13485 or in the aerospace industry can be offered exclusively with customer-specific, individual agreements by SCHURTER.






**Application standards**

Application standards where the product can be used

| Organization | Design                         | Standard       | Description  |
|--------------|--------------------------------|----------------|--|
|              | Suitable for applications acc. | IEC/UL 62368-1 | Audio/video, information and communication technology equipment - Part 1: Safety requirements  |
|              | Suitable for applications acc. | IEC 60601-1    | Medical electrical equipment - Part 1: General requirements for basic safety and essential performance   |
|              | Suitable for applications acc. | IEC 60335-1    | Safety of electrical appliances for household and similar purposes. Meets the requirements for appliances in unattended use. This includes the enhanced requirements of glow wire tests acc. to IEC 60695-2-11 or -12 & -13. |

## Compliances

The product complies with following Guide Lines

| Identification   | Details                    | Initiator   | Description   |
|--|----------------------------|-------------|---|
|  | RoHS                       | SCHURTER AG | Directive RoHS 2011/65/EU, Amendment (EU) 2015/863  |
|  | China RoHS                 | SCHURTER AG | The law SJ / T 11363-2006 (China RoHS) has been in force since 1 March 2007. It is similar to the EU directive RoHS.  |
|  | REACH                      | SCHURTER AG | On 1 June 2007, Regulation (EC) No 1907/2006 on the Registration, Evaluation, Authorization and Restriction of Chemicals 1 (abbreviated as "REACH") entered into force. |
|  | White Paper Glow wire test | SCHURTER AG | Meets the requirements of IEC 60335-1 for appliances in unattended use. This includes the enhanced requirements of glow wire tests acc. to IEC 60695-2-11 or -12 &-13.  |
|  | Medical Equipment          | SCHURTER AG | Suitable for use in medical equipment according to IEC/UL 60601-1 (1 MOOP, 1 MOPP)  |

## Voltage Selector Inserts

| yy           | KEC<br>KD | Marking on Voltage Selector Insert / Terminal No. |        |        |        |
|--------------|-----------|---|--------|--------|--------|
|              |           | 1<br>3  | 2<br>4 | 3<br>5 | 4<br>6 |
| 4303.2014.00 |           | -   | -      | -      | -      |
| 4303.2014.01 |           | 100   | 120    | 220    | 240    |
| 4303.2014.02 |           | 110   | 150    | 220    | -      |
| 4303.2014.03 |           | 110   | -      | 220    | -      |
| 4303.2014.04 |           | 110   | 220    | 240    | -      |
| 4303.2014.05 |           | 115   | -      | 230    | -      |
| 4303.2014.06 |           | 117   | 220    | 240    | -      |
| 4303.2014.08 |           | 110 V   | -      | 220 V  | -      |
| 4303.2014.09 |           | 220   | -      | 240    | -      |
| 4303.2014.11 |           | 110   | 120    | 220    | 240    |
| 4303.2014.12 |           | 115   | 230    | 240    | -      |
| 4303.2014.13 |           | 100   | 110    | 220    | 240    |
| 4303.2014.14 |           | 100   | 117    | 220    | 240    |
| 4303.2014.15 |           | 100   | 115    | 230    | -      |
| 4303.2014.16 |           | 100   | 120    | 230    | 240    |
| 4303.2014.17 |           | 115   | 120    | 230    | 240    |
| 4303.2014.19 |           | 220   | 120    | 240    | 230    |
| 4303.2014.20 |           | 100   | 120    | 230    | -      |
| 4303.2014.21 |           | 100   | -      | 220    | -      |
| 4303.2014.22 |           | 100   | 120    | 220    | 230    |
| 4303.2014.24 |           | 200   | 220    | 240    | -      |
| 4303.2014.27 |           | 115   | 200    | 230    | -      |
| 4303.2014.32 |           | 100   | 110    | 230    | 240    |
| 4303.2014.34 |           | 110   | 115    | 230    | 240    |
| 4303.2014.35 |           | 100   | 115    | 230    | 240    |
| 4303.2014.36 |           | 100   | 110    | 200    | 230    |
| 4303.2014.42 |           | 100   | 115    | 120    | 230    |
| 4303.2014.46 |           | 100   | 120    | 200    | 230    |
| 4303.2024.00 |           | -   | -      | -      | -      |
| 4303.2024.01 |           | 100   | 120    | 220    | 240    |
| 4303.2024.02 |           | 110   | 150    | 220    | -      |
| 4303.2024.03 |           | 110   | -      | 220    | -      |
| 4303.2024.04 |           | 110   | 220    | 240    | -      |
| 4303.2024.05 |           | 115   | -      | 230    | -      |
| 4303.2024.06 |           | 117   | 220    | 240    | -      |
| 4303.2024.08 |           | 110 V   | -      | 220 V  | -      |
| 4303.2024.09 |           | 220   | -      | 240    | -      |
| 4303.2024.10 |           | 115   | 220    | 240    | -      |
| 4303.2024.11 |           | 110   | 120    | 220    | 240    |
| 4303.2024.12 |           | 115   | 230    | 240    | -      |

| yy             | KEC<br>KD | Marking on Voltage Selector Insert / Terminal No. |        |        |        |
|----------------|-----------|---|--------|--------|--------|
|                |           | 1<br>3  | 2<br>4 | 3<br>5 | 4<br>6 |
| 4303.2024.15   |           | 100   | 115    | 230    | -      |
| 4303.2024.16   |           | 100   | 120    | 230    | 240    |
| 4303.2024.17   |           | 115   | 120    | 230    | 240    |
| 4303.2024.18   |           | 115   | -      | 240    | -      |
| 4303.2024.19   |           | 220   | 120    | 240    | 230    |
| 4303.2024.20   |           | 100   | 120    | 230    | -      |
| 4303.2024.22   |           | 100   | 120    | 220    | 230    |
| 4303.2024.25   |           | 120   | -      | 230    | -      |
| 4303.2024.28   |           | -   | 230    | 240    | -      |
| 4303.2024.30   |           | 117   | 220    | 240    | 100    |
| 4303.2024.31   |           | 117   | 220    | 240    | 100    |
| 4303.2024.35   |           | 100   | 115    | 230    | 240    |
| 4303.2024.40   |           | 100   | 110    | 127    | 230    |
| 4303.2024.44   |           | 100   | 115    | 127    | 230    |
| 4303.2024.45   |           | 100   | 115    | 230    | 127    |
| 4303.2024.46   |           | 100   | 120    | 200    | 230    |
| 4303.2036.01   |           | 100   | 120    | 220    | 240    |
| 4303.2036.01.1 |           | 100   | 120    | 220    | 240    |
| 4303.2036.03   |           | 110   | -      | 220    | -      |
| 4303.2036.04   |           | 110   | 220    | 240    | -      |
| 4303.2036.05   |           | 115   | -      | 230    | -      |
| 4303.2036.11   |           | 110   | 120    | 220    | 240    |
| 4303.2036.23   |           | 100   | 110    | 120    | -      |
| 4303.2037.01   |           | 100   | 120    | 220    | 240    |
| 4303.2037.03   |           | 110   | -      | 220    | -      |
| 4303.2037.10   |           | 115   | 220    | 240    | -      |
| 4303.2037.13   |           | 100   | 110    | 220    | 240    |
| 4303.2114.01   |           | 100   | 120    | 220    | 240    |
| 4303.2114.02   |           | 110   | 150    | 220    | -      |
| 4303.2114.03   |           | 110   | -      | 220    | -      |
| 4303.2114.04   |           | 110   | 220    | 240    | -      |
| 4303.2114.05   |           | 115   | -      | 230    | -      |
| 4303.2114.08   |           | 110 V   | -      | 220 V  | -      |
| 4303.2114.09   |           | 220   | -      | 240    | -      |
| 4303.2114.11   |           | 110   | 120    | 220    | 240    |
| 4303.2114.12   |           | 115   | 230    | 240    | -      |
| 4303.2114.13   |           | 100   | 110    | 220    | 240    |
| 4303.2114.15   |           | 100   | 115    | 230    | -      |
| 4303.2114.17   |           | 115   | 120    | 230    | 240    |
| 4303.2114.20   |           | 100   | 120    | 230    | -      |
| 4303.2114.22   |           | 100   | 120    | 220    | 230    |
| 4303.2114.29   |           | 100   | 117    | 125    | -      |
| 4303.2114.43   |           | 115   | -      | 230    | -      |
| 4303.2114.48   |           | 100   | 120    | 208    | 230    |
| 4303.2124.00   |           | -   | -      | -      | -      |
| 4303.2124.01   |           | 100   | 120    | 220    | 240    |
| 4303.2124.02   |           | 110   | 150    | 220    | -      |
| 4303.2124.03   |           | 110   | -      | 220    | -      |
| 4303.2124.04   |           | 110   | 220    | 240    | -      |
| 4303.2124.05   |           | 115   | -      | 230    | -      |
| 4303.2124.12   |           | 115   | 230    | 240    | -      |
| 4303.2124.15   |           | 100   | 115    | 230    | -      |
| 4303.2124.16   |           | 100   | 120    | 230    | 240    |
| 4303.2124.19   |           | 220   | 120    | 240    | 230    |

| yy           | KEC<br>KD | Marking on Voltage Selector Insert / Terminal No. |        |        |        |
|--------------|-----------|---|--------|--------|--------|
|              |           | 1<br>3  | 2<br>4 | 3<br>5 | 4<br>6 |
| 4303.2124.22 |           | 100   | 120    | 220    | 230    |
| 4303.2124.23 |           | 100   | 110    | 120    | -      |
| 4303.2124.37 |           | 115   | 230    | 240    | 100    |
| 4303.2124.39 |           | 220   | 230    | 240    | -      |
| 4303.2401    |           | -   | -      | -      | -      |
| 4303.2403    |           | -   | -      | -      | -      |
| 4303.2406    |           | -   | -      | -      | -      |
| 4303.2408    |           | -   | -      | -      | -      |
| 4303.2411    |           | -   | -      | -      | -      |
| 4303.2413    |           | -   | -      | -      | -      |
| 4303.2416    |           | -   | -      | -      | -      |
| 4303.2514.01 |           | 100   | 120    | 220    | 240    |
| 4303.2514.02 |           | 110   | 150    | 220    | -      |
| 4303.2514.03 |           | 110   | -      | 220    | -      |
| 4303.2514.05 |           | 115   | -      | 230    | -      |
| 4303.2514.08 |           | 110 V   | -      | 220 V  | -      |
| 4303.2514.15 |           | 100   | 115    | 230    | -      |
| 4303.2514.16 |           | 100   | 120    | 230    | 240    |
| 4303.2514.17 |           | 115   | 120    | 230    | 240    |
| 4303.2514.18 |           | 115   | -      | 240    | -      |
| 4303.2514.23 |           | 100   | 110    | 120    | -      |
| 4303.2514.38 |           | 110   | 230    | 220    | 240    |
| 4303.2524.01 |           | 100   | 120    | 220    | 240    |
| 4303.2524.04 |           | 110   | 220    | 240    | -      |
| 4303.2524.05 |           | 115   | -      | 230    | -      |
| 4303.2524.16 |           | 100   | 120    | 230    | 240    |
| 4303.2524.20 |           | 100   | 120    | 230    | -      |
| 4303.2524.23 |           | 100   | 110    | 120    | -      |
| 4303.2524.25 |           | 120   | -      | 230    | -      |
| 4303.2536.46 |           | 100   | 120    | 200    | 230    |
| 4303.2537.46 |           | 100   | 120    | 200    | 230    |
| 4303.2614.01 |           | 100   | 120    | 220    | 240    |
| 4303.2614.02 |           | 110   | 150    | 220    | -      |
| 4303.2614.03 |           | 110   | -      | 220    | -      |
| 4303.2614.04 |           | 110   | 220    | 240    | -      |
| 4303.2614.09 |           | 220   | -      | 240    | -      |
| 4303.2614.15 |           | 100   | 115    | 230    | -      |
| 4303.2614.23 |           | 100   | 110    | 120    | -      |
| 4303.2614.28 |           | -   | 230    | 240    | -      |
| 4303.2624.01 |           | 100   | 120    | 220    | 240    |
| 4303.2624.03 |           | 110   | -      | 220    | -      |
| 4303.2624.04 |           | 110   | 220    | 240    | -      |
| 4303.2624.22 |           | 100   | 120    | 220    | 230    |
| 4303.2714.08 |           | 110 V   | -      | 220 V  | -      |
| 4303.2737.01 |           | 100   | 120    | 220    | 240    |
| 4303.2737.05 |           | 115   | -      | 230    | -      |
| 4303.2737.06 |           | 117   | 220    | 240    | -      |
| 4303.2901    |           | -   | -      | -      | -      |
| 4303.2903    |           | -   | -      | -      | -      |
| 4303.2906    |           | -   | -      | -      | -      |
| 4303.2908    |           | -   | -      | -      | -      |
| 4303.2911    |           | -   | -      | -      | -      |
| 4303.2913    |           | -   | -      | -      | -      |

Index "yy" matches the last two characters of the Order Number within the Variants

All Variants

| Mounting   | Fuse-Link | Fuseholder | Comment         | Order Number |
|------------|-----------|------------|-----------------|--------------|
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.01 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.02 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.03 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.04 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.05 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.08 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.09 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.11 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.12 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.15 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.17 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.20 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.22 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.29 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.43 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2114.48 |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2124.00 |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2124.01 |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2124.03 |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2124.04 |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2124.05 |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2124.12 |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2124.15 |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2124.19 |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2124.22 |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2124.23 |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2124.37 |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2124.39 |
| Fingergrip | 5 x 20    | 1-pole     | -               | 4303.2406    |
| Extra-Safe | 5 x 20    | 1-pole     | -               | 4303.2408    |
| Fingergrip | 5 x 20    | 1-pole     | spare fuse case | 4303.2416    |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.00 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.01 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.02 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.03 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.04 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.05 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.06 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.08 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.09 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.11 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.12 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.13 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.15 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.16 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.17 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.19 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.20 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.21 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.22 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.24 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.27 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.34 |
| Fingergrip | 5 x 20    | 2-pole     | -               | 4303.2014.35 |

| Mounting   | Fuse-Link | Fuseholder | Comment                          | Order Number   |
|------------|-----------|------------|----------------------------------|----------------|
| Fingergrip | 5 x 20    | 2-pole     | -                                | 4303.2014.36   |
| Fingergrip | 5 x 20    | 2-pole     | -                                | 4303.2014.42   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.00   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.01   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.02   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.03   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.04   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.05   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.06   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.08   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.09   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.10   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.11   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.12   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.15   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.16   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.17   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.18   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.19   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.20   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.22   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.25   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.28   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.30   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.35   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.40   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.44   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.45   |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.46   |
| Fingergrip | 5 x 20    | 2-pole     | -                                | 4303.2401      |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2403      |
| Fingergrip | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2036.01   |
| Fingergrip | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2036.01.1 |
| Fingergrip | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2036.03   |
| Fingergrip | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2036.04   |
| Fingergrip | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2036.05   |
| Fingergrip | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2036.11   |
| Fingergrip | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2036.23   |
| Extra-Safe | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2037.01   |
| Extra-Safe | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2037.03   |
| Extra-Safe | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2037.10   |
| Extra-Safe | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2037.13   |
| Fingergrip | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2411      |
| Extra-Safe | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2413      |
| Fingergrip | 6.3 x 32  | 1-pole     | -                                | 4303.2614.01   |
| Fingergrip | 6.3 x 32  | 1-pole     | -                                | 4303.2614.02   |
| Fingergrip | 6.3 x 32  | 1-pole     | -                                | 4303.2614.03   |
| Fingergrip | 6.3 x 32  | 1-pole     | -                                | 4303.2614.04   |
| Fingergrip | 6.3 x 32  | 1-pole     | -                                | 4303.2614.09   |
| Fingergrip | 6.3 x 32  | 1-pole     | -                                | 4303.2614.23   |
| Fingergrip | 6.3 x 32  | 1-pole     | -                                | 4303.2614.28   |
| Extra-Safe | 6.3 x 32  | 1-pole     | -                                | 4303.2624.01   |
| Extra-Safe | 6.3 x 32  | 1-pole     | -                                | 4303.2624.03   |
| Extra-Safe | 6.3 x 32  | 1-pole     | -                                | 4303.2624.04   |
| Extra-Safe | 6.3 x 32  | 1-pole     | -                                | 4303.2624.22   |

| Mounting   | Fuse-Link | Fuseholder | Comment                          | Order Number |
|------------|-----------|------------|----------------------------------|--------------|
| Fingergrip | 6.3 x 32  | 1-pole     | -                                | 4303.2906    |
| Extra-Safe | 6.3 x 32  | 1-pole     | -                                | 4303.2908    |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2514.01 |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2514.02 |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2514.03 |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2514.05 |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2514.08 |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2514.15 |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2514.16 |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2514.17 |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2514.18 |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2514.23 |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2514.38 |
| Extra-Safe | 6.3 x 32  | 2-pole     | -                                | 4303.2524.01 |
| Extra-Safe | 6.3 x 32  | 2-pole     | -                                | 4303.2524.04 |
| Extra-Safe | 6.3 x 32  | 2-pole     | -                                | 4303.2524.05 |
| Extra-Safe | 6.3 x 32  | 2-pole     | -                                | 4303.2524.16 |
| Extra-Safe | 6.3 x 32  | 2-pole     | -                                | 4303.2524.20 |
| Extra-Safe | 6.3 x 32  | 2-pole     | -                                | 4303.2524.23 |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2901    |
| Extra-Safe | 6.3 x 32  | 2-pole     | -                                | 4303.2903    |
| Fingergrip | 6.3 x 32  | 2-pole     | shorting bar on the neutral side | 4303.2536.46 |
| Extra-Safe | 6.3 x 32  | 2-pole     | shorting bar on the neutral side | 4303.2537.46 |
| Fingergrip | 6.3 x 32  | 2-pole     | shorting bar on the neutral side | 4303.2911    |
| Extra-Safe | 6.3 x 32  | 2-pole     | shorting bar on the neutral side | 4303.2913    |

Most Popular.

Availability for all products can be searched real-time: <https://www.schurter.com/en/info-center/support-tools/stock-check-distributors>

"yy" see Voltage Selector Inserts Table

(Packaging unit for article 4303.2401 and 4303.2403 = 50pcs.)

**Packaging unit** 10 Pcs